

■ Simple Socket Ordering Information:

P I - 35 - 0

Suit State:

Nil: for Socket Terminal Socket
0: for PCB Terminal Socket

Effective Holes and Suit Dimension:

05: 5 Holes
08: 8 Holes
11: 11 Holes
14: 14 Holes
35: 3.5mm
50: 5.0mm

Suit Relay Model:

Y: RE Model
T: RET Model
I: EMI, EZ Model
L: LR Model

Item:

P: Socket

◇ Simple Socket List

No	Socket Name	Suit Relay Model	Note
1	PI-35-0	EMI-1P, MI-1P	PCB Terminal
2	PI-50-0	EMI-2P, MI-2P, EZ, EZI	PCB Terminal

Socket illustration

PI-35-0



BP-15/20/25-MS
(15/20/25mm)



(Metal)



BP-15/20/25-PS
(15/20/25mm)

(Plastic)

Equipment



Appearance illustration

PI-50-0



BP-15/20/25-MS
(15/20/25mm)



(Metal)



BP-15/20/25-PS
(15/20/25mm)

(Plastic)

Equipment



Appearance illustration